

"RELAYS"

NO.	COIL NO.	TYPE	CONTACTS	USE
B	A-9735	AG.	4A	POP BUMPER RELAY
C	A-9735	AG.	4A	500 POINT & SPIN ROTO UNIT RELAY
D	A-9735	AG.	3A, 1C	SPECIAL ROLLOVER RELAY
E	A-9735	AG.	5A	HOLE & SPIN ROTO UNIT RELAY
F	A-489	AS.	2 DISC	00-90 UNIT RELAY
G	A-9735	AG.	3A	ROTO UNIT SCORE CONTROL RELAY
L	A-9735	AG.	5A	1000 POINT RELAY
M	A-9735	AG.	4A	100 POINT RELAY
N	A-9735	AG.	4A	10 POINT RELAY
O	A-9735	AG.	5A, 1B	BALL RETURN RELAY
Q	A-9746	AG.	1A	SERIES RELAY
R	A-9738	AG.	3A, 1B, 1C	HOLD RELAY
S	A-9740	AG.	2A, 2C	START RELAY
T	A-9742	AG.	1B	TILT RELAY
W	A-9740	AG.	2A, 1B, 1C	2ND, CHUTE RELAY
AX	A-9735	INTER-	5A, 1B	RESET COMPLETED RELAY
AXR	A-5662	LOCK		

"SEQUENCE BANK"

NO.	COIL NO.	CONTACTS	USE
8B	A-1118	2B	#1-#4 SEQUENCE COMPLETED RELAY
1B	A-1119	3A	#1 ROTO TARGET RELAY
2B	A-1119	3A	#2 ROTO TARGET RELAY
10B	A-1118	2B	#3-#6 SEQUENCE COMPLETED RELAY
3B	A-1119	5A	#3 ROTO TARGET RELAY
4B	A-1119	3A	#4 ROTO TARGET RELAY
5B	A-1119	5A	#5 ROTO TARGET RELAY
9B	A-1118	2B	#2-#5 SEQUENCE COMPLETED RELAY
6B	A-1119	3A	#6 ROTO TARGET RELAY
7B	A-1119	3A	#7 ROTO TARGET RELAY
11B	A-1118	2B	#4-#7 SEQUENCE COMPLETED RELAY
12B	A-1118	2B	SPECIAL ROLLOVER CONTROL RELAY

"SEQUENCE BANK"

NO.	COIL NO.	CONTACTS	USE
13B	A-1118	2A, 1B, 2C	"A" ROLLOVER RELAY
14B	A-1118	2A, 1B, 2C	"B" ROLLOVER RELAY
17B	NO COIL	2A	A-D SEQUENCE COMPLETED SWITCHES
15B	A-1118	2A, 1B, 2C	"C" ROLLOVER RELAY
16B	A-1118	2A, 1B, 2C	"D" ROLLOVER RELAY